




HF RFID TIME MACHINE

Features

- ISO/IEC 15693 compliance
- On board antenna
- RTC
- 2 M bit Memory
- RS232 Serial Port
- Visual and Audio Indication

Applications

- Office time and attendance management



Description


Pico RFID line of HF 13.56 MHz Time Machine readers brings the efficiency in office time and attendance management system.

The Time Machine is based on Texas Instruments RFID technology and operates at 13.56 MHz Frequency, which is compliance with the ISO/IEC 15693 vicinity card standards. Its features includes a printed antenna, a Real Time Clock (RTC), 2 M bit memory. With these features the Time Machine can work as a slave to a host PC or work as a stand alone device in the absence of the host.

The reader has a RS232 communication port for interfacing with the PC with a configurable baud rate. Two LED's and a buzzer are used for visual and audio communication.

For more information, please contact www.pico-mega.com

Pico Mega reserves the rights to change its products and services at any time without notice. Pico Mega assumes no responsibility for customer product design or for infringement of patents and / or the rights of third parties, which may result from assistance provided by Pico Mega.



Specifications

Part Number	ID-HF2A-TM1A
Operating frequency	13.56 MHz
Supported transponder standard	ISO/IEC 15693
Supply voltage	+6.5 V to +12 V DC
Current consumption	150 mA (peak)
Transmitter power level	200 mW (pulsed)
Antenna connection	On board PCB antenna
Antenna impedance	50 ohms @ 13.56 MHz
Communication interface	RS232
Baud rate	Configurable from 300 bps to 57600 bps*.
Protocol	Pico protocol
Visual / Audio Interface	Two LED's and a Buzzer
Additional features	Inbuilt Real Time Clock (RTC) Inbuilt Memory of 2 M bits
Operating temperature	-20°C to + 65°C
Storage temperature	-40°C to + 85°C
Dimensions	110(L) x 80(W) x 38(H) all in mm
Weight	175 grams

* The reader supports baud rate from 300 bps to 57600 bps except 38400. Please refer the Reference manual of 'Pico RFID Time Machine' for more information.

Pico Mega Design Labs reserves the right to change its products and services at any time without notice. Pico Mega Design Labs provides customer assistance in various technical areas, but does not have full access to data concerning the uses and applications of customer's solutions. Therefore, Pico Mega assumes no responsibility for customer solution design or for infringement of patents and/or the rights of third parties, which may result from assistance provided by Pico Mega Design Labs.